



## Upgrading to Contour 2.x from Version 1.6 or Higher

*This information is subject to change without notice and is provided "as is" with no warranty. Optek specifically disclaims liability for any direct, indirect, special, incidental, or consequential damages in connection with the use of this material.*

### Installing the Upgrade

1. On the Contour main screen, click **Configure** to open the Configuration Utility.
2. Click **Tools > Database Connection** to open the SQL Connection dialog.
3. Click **OK**.
4. Close the Configuration Utility window.
5. Using the Contour keyboard, press **Shift+F1** to open Windows Explorer.
6. Press **Alt+Tab** to toggle back to the Contour control software.
7. Press **Ctrl+Alt+X** to close Contour control software.
8. Insert the software CD into the CD-ROM drive.
9. After a few moments, the Contour 2.x Installation screen will open.
10. Click **Upgrade Existing Software**.
11. Follow instructions on screen and choose **Complete** when prompted for the type of installation.
12. When upgrade is complete, click **Finish**. Windows Explorer will be visible.
13. Double-click the **Contour Machine Control** shortcut on the Desktop.
14. The License Activation screen will now be displayed.
15. Using the mouse, click the **Manual** activation method.
16. Enter the serial number provided with your installation media.
17. Contact Optek with the Request Code that is generated by Contour.
18. You will be provided with an Activation Key. This number must be entered exactly as provided.
19. Click **Activate**.

**License Activation**

Select an activation method

Online  
Choose this option if you have an Internet connection.

**Manual**  
Choose this option if you do not have an Internet connection or are having difficulties completing online activation. To obtain an activation key:  
Call Optek Customer Service at 1-727-525-2153 or 1-800-524-5454

Activation key codes

Request code  
Your request code will be here

Serial number (provided with your installation media)  
Type your serial number here

Activation key (provided at activation)

Activate Cancel

## ***Updating Your Configuration Settings***

Contour 2.x contains many enhancements. In order to realize its full potential, the configuration file has been modified. Most configuration changes are automatically updated during installation, but any custom settings will need to be manually adjusted.

On the Contour main screen, click **Configure**. Follow the directions below to modify settings.

### ***Machines***

1. Click the **5. Machines** tab.
2. Double-click the appropriate machine record.
3. Click **Edit**.
4. How is the Contour connected to the lab computer?
  - a. Ethernet: Continue with step 5.
  - b. Serial cable: Skip to step 7.
5. Click the **2. Host Interface** tab.
6. Add **:6711** directly after the existing value in the **Server name/address:port** field.
7. Click the **3. Defaults** tab.
8. Change the Lap Tool Style to **Foam, 0 Base**.
9. Click **OK** to save changes and close the window.

### ***Lens Materials***

1. Click the **1. Lens Materials** tab.
2. For each material, double click the material name and click **Edit**.
3. For High Index and Plastic CR-39...
  - a. Under Cut Depth (mm), change Center protect to **0.00**.
  - b. Click **OK** to save changes and close the window.
4. For Polycarbonate and Trivex...
  - a. Under Cut Depth (mm), change Center protect to **0.40**.
  - b. Click **OK** to save changes and close the window.

### ***Lap Tool Styles***

1. Click the **2. Laps Tool Styles** tab.
2. Double-click the **Foam, 0 Base** entry.
3. Click **Edit**.
4. Under Cut Depth (mm), change both Rough and Finish to **10.00**.
5. Click **OK** to save changes and close the window.
6. Optek has standardized our offering of foam laps to the 0 Base only.
  - a. Select all entries for foam tool bases other than 0 Base and click **Delete**.
  - b. Click **Yes** to confirm deletion.

### ***Configuration Options***

1. On the Configuration Utility main menu, select **Tools | Options**.
2. Set Max. lap tool height (mm) to **36**.
3. If you have not entered your lab name and phone number in the Lab Name field, please do so. This will assist our customer support department when using the Diagnostic report.
4. Click **OK** to save changes and close the window.
5. Finally, close the configuration utility to return to the Contour control screen.